

# GOODWE

## BT Series

### 5-10kW | Three Phase AC-Coupled HV Retrofit Inverter

The BT series is a GoodWe retrofit AC coupled solution, which is able to upgrade existing three-phase PV systems to storage systems of 5kW, 6kW, 8kW & 10kW. This solution is able to modernize any three-phase PV system, providing the ability to store power or operate with the back-up of batteries, ensuring interactivity or grid independence. It is compatible with high voltage Li-Ion batteries ranging from 180 to 600V and is also equipped with UPS function. As part of its set of protections, it incorporates a Battery Input Reverse Polarity Protection.



8 ms UPS-level Switching



110% AC output overloading



High voltage battery (180-600V)



Battery Input Reverse Polarity Protection

Technical Data	GW5K-BT	GW6K-BT	GW8K-BT	GW10K-BT
<b>Battery Input Data</b>				
Battery Type	Li-Ion	Li-Ion	Li-Ion	Li-Ion
Nominal Battery Voltage (V)	500	500	500	500
Battery Voltage Range (V)	180~600	180~600	180~600	180~600
Max. Continuous Charging Current (A)	25	25	25	25
Max. Continuous Discharging Current (A)	25	25	25	25
Max. Charging Power (W)	5000	6000	8000	10000
Max. Discharging Power (W)	5000	6000	8000	10000
<b>AC Output Data (On-grid)</b>				
Nominal Apparent Power Output to Utility Grid (VA)	5000	6000	8000	10000
Max. Apparent Power Output to Utility Grid (VA) <sup>1,4</sup>	5500	6600	8800	11000
Max. Apparent Power from Utility Grid (VA)	10000	12000	15000	15000
Nominal Output Voltage (V)	400/380, 3L/N/PE	400/380, 3L/N/PE	400/380, 3L/N/PE	400/380, 3L/N/PE
Nominal AC Grid Frequency (Hz)	50/60	50/60	50/60	50/60
Max. AC Current Output to Utility Grid (A)	8.5	10.5	13.5	16.5
Max. AC Current From Utility Grid (A)	15.2	18.2	22.7	22.7
Power Factor	~1 (Adjustable from 0.8 leading to 0.8 lagging)			
Max. Total Harmonic Distortion	<3%	<3%	<3%	<3%
<b>AC Output Data (Back-up)</b>				
Back-up Nominal Apparent Power (VA)	5000	6000	8000	10000
Max. Output Apparent Power (VA)	5000 (10000@60sec)	6000 (12000@60sec)	8000 (15000@60sec)	10000 (15000@60sec)
Max. Output Current (A)	8.5	10.5	13.5	16.5
Nominal Output Voltage (V)	400/380, 3L/N/PE	400/380, 3L/N/PE	400/380, 3L/N/PE	400/380, 3L/N/PE
Nominal Output Frequency (Hz)	50/60	50/60	50/60	50/60
Output THDv (@Linear Load)	<3%	<3%	<3%	<3%
<b>Efficiency</b>				
Max. Efficiency	97.6%	97.6%	97.6%	97.6%
European Efficiency	97.2%	97.2%	97.5%	97.5%
Max. Battery to AC Efficiency	97.6%	97.6%	97.6%	97.6%
<b>Protection</b>				
PV Insulation Resistance Detection	Integrated	Integrated	Integrated	Integrated
Residual Current Monitoring	Integrated	Integrated	Integrated	Integrated
Battery Reverse Polarity Protection	Integrated	Integrated	Integrated	Integrated
Anti-islanding Protection	Integrated	Integrated	Integrated	Integrated
AC Overcurrent Protection	Integrated	Integrated	Integrated	Integrated
AC Short Circuit Protection	Integrated	Integrated	Integrated	Integrated
AC Overvoltage Protection	Integrated	Integrated	Integrated	Integrated
<b>General Data</b>				
Operating Temperature Range (°C)	-35~+60	-35~+60	-35~+60	-35~+60
Relative Humidity	0~95%	0~95%	0~95%	0~95%
Max. Operating Altitude (m)	4000	4000	4000	4000
Cooling Method	Natural Convection	Natural Convection	Natural Convection	Natural Convection
User Interface	LED & APP	LED & APP	LED & APP	LED & APP
Communication with BMS <sup>2</sup>	RS485, CAN	RS485, CAN	RS485, CAN	RS485, CAN
Communication with Meter	RS485	RS485	RS485	RS485
Communication with Portal	WiFi, LAN	WiFi, LAN	WiFi, LAN	WiFi, LAN
Weight (kg)	21	21	21	21
Dimension (WxHxD mm)	415 x 516 x 180	415 x 516 x 180	415 x 516 x 180	415 x 516 x 180
Topology	Non-isolated	Non-isolated	Non-isolated	Non-isolated
Self-consumption at Night (W) <sup>3</sup>	<15	<15	<15	<15
Ingress Protection Rating	IP66	IP66	IP66	IP66
Mounting Method	Wall Mounted	Wall Mounted	Wall Mounted	Wall Mounted

\*1: According to the local grid regulation..

\*2: CAN communication is configured by default. If 485 communication is used, please replace the corresponding communication line.

\*3: No Back-up Output.

\*4: For Belgium Max. Apparent Power Output to Utility Grid (VA): GW5K-BT is 5000; GW6K-BT is 6000; GW8K-BT is 8000; GW10K-BT is 10000.

\*: Peak output apparent power can be reached only if PV and battery power is enough.

\*: AFDPF: Active Frequency Drift with Positive Feedback, AQDPF: Active Q Drift with Positive Feedback.

\*: Please visit GoodWe website for the latest certificates